

BTR 700 CHANNEL MAP												A2 Band												
Base Tx		22		23		24																		
		518	524	524	530	530	536																	
Bp Tx		41		42		43																		
		632	638	638	644	644	650																	
Pair Groups = 24 (12a + 12b)																								
Group	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b	9a	9b	10a	10b	11a	11b	12a	12b
Tx	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24	22	22	23	23	24	24
1	522.3	521.5	528.3	527.5	534.3	533.5	522.6	520.7	528.6	527.7	534.6	533.7	523.3	520.6	529.4	526.4	534.6	533.7	522	522.7	528	528.7	534	534.7
Rx	41,42,43		41,42,43		41,42,43		41,42		41,42		41,42		42,43		42,43		42,43		41,43		41,43		41,43	
1	632.2	632.2	632.2	632.2	632.2	632.2	632.5	632.5	632.5	632.5	632.5	632.5	638.5	638.5	638.5	638.5	638.5	638.5	632.1	632.1	632.1	632.1	632.1	632.1
2	632.7	632.7	632.7	632.7	632.7	632.7	632.8	632.8	632.8	632.8	632.8	632.8	638.8	638.8	638.8	638.8	638.8	638.8	632.4	632.4	632.4	632.4	632.4	632.4
3	634.5	634.5	634.5	634.5	634.5	634.5	633.3	633.3	633.3	633.3	633.3	633.3	640.7	640.7	639.9	639.9	639.3	639.3	632.9	632.9	632.9	632.9	632.9	632.9
4	637	637	637	637	637	637	635.6	635.6	635.6	635.6	635.6	635.6	642	642	642	642	641.6	641.6	635.2	635.2	635.2	635.2	635.2	635.2
5	640	640	640	640	640	640	637.6	637.6	637.6	637.6	637.6	637.6	644.3	644.3	644	644	643.6	643.6	636.9	636.9	636.9	636.9	636.9	636.9
6	643.5	643.5	643.5	643.5	643.5	643.5	640.1	640.1	640.1	640.1	640.1	640.1	646.3	646.3	646.5	646.5	646.1	646.1	637.8	637.8	637.8	637.8	637.8	637.8
7	644.7	644.7	644.7	644.7	644.7	644.7	641.3	641.3	641.3	641.3	641.3	641.3	648	648	648.8	648.8	647.3	647.3	644.5	644.5	644.5	644.5	644.5	644.5
8	648.4	648.4	648.4	648.4	648.4	648.4	642.8	642.8	642.8	642.8	642.8	642.8	648.8	648.8	649.6	649.6	648.8	648.8	647.5	647.5	647.5	647.5	647.5	647.5
9	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
10	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
Single Groups = 12																								
Group	13	14	15	16	17	18	19	20	21	22	23	24												
Tx	22	23	24	22	23	24	22	23	24	22	23	24												
1	521.5	527.1	533.7	522.6	528.6	534.6	522.6	528.6	534.6	522.6	528.6	534.6												
Rx	41,42,43	41,42,43	41,42,43	41	41	41	42	42	42	43	43	43												
1	632.1	632.2	632.3	632.2	632.2	632.2	638.2	638.2	638.2	644.2	644.2	644.2												
2	632.5	632.7	632.7	632.7	632.7	632.7	638.7	638.7	638.7	644.7	644.7	644.7												
3	634.4	636.3	635	633.4	633.4	633.4	639.4	639.4	639.4	645.4	645.4	645.4												
4	637.8	637.5	637.5	636.1	636.1	636.1	642.1	642.1	642.1	648.1	648.1	648.1												
5	641.5	641.2	643	---	---	---	---	---	---	---	---	---												
6	642.9	644.1	644.7	---	---	---	---	---	---	---	---	---												
7	645.9	646.6	647.7	---	---	---	---	---	---	---	---	---												
8	647.1	649.6	649.6	---	---	---	---	---	---	---	---	---												
9	---	---	---	---	---	---	---	---	---	---	---	---												
10	---	---	---	---	---	---	---	---	---	---	---	---												
NOTES:																								
1) Groups 25 - 36 are user-programmable and are blank initially.																								
2) The BTR-700 band plan is the same as the BTR-800 except BTR-800 transmitter 1 (Ch A) frequencies are not used.																								
3) "---" = Blank																								
4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.																								

B4 Band

- 1) Groups 25 - 36 are user-programmable and are blank initially.
- 2) The BTR-700 band plan is the same as the BTR-800 except BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "-" = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.

C3 Band

- 1) Groups 25 - 36 are user-programmable and are blank initially.
- 2) The BTR-700 band plan is the same as the BTR-800 except BTR-800 transmitter 1 (Ch A) frequencies are not used.
- 3) "..." = Blank
- 4) Pair Groups are Intermodulation Coordinated. Example 1a, 1b may be used together.

